


APG / Active Audio – Service Procedure

INITIALIZING AN AMPLIFIER FOR USE WITH AMI SOFTWARE

Cloudpower MPA/DA Amplifier




	<p>IMPORTANT : The procedure below will completely <u>delete the current state and existing data from the amplifier.</u></p> <p>If the device is already in use in an existing installation, it is therefore essential to manually note <u>ALL</u> existing parameters (EQ, delays, levels, preset used, etc.), in order to manually transfer them later in AMi.</p>
---	---


1. PREREQUISITES: REQUIRED FILE

Before performing the manipulation, it is necessary to have the "ami-amp-config.exe" initialization file downloadable online by following the instructions below:

- Go to the website: <https://ami.arbane-groupe.com/ami/quickstart/index.html>
- Click on "AMI Support Tools" at the bottom of the page:




- Click on "Download" to download the file:



2. CONNECTING THE AMPLIFIER AND CONFIGURING THE NETWORK

- **Connect** a PC Windows computer via a **network cable directly** to the amplifier. ONLY one amplifier should be connected at a time.
- **Disable WiFi** on the computer to avoid conflicts.
- **Configure the computer in fixed iP** on the wired (Ethernet) network :
(e.g. iP 192.168.0.11 / subnet 255.255.0.0)




- **Configure the amplifier in fixed iP (STATIC)** via the network menu:
(e.g. iP 192.168.0.1 / subnet 255.255.0.0)




- **IMPORTANT:** The receiver and computer must be on the same iP range with the same subnet mask to communicate

3. UPDATING AND INITIALIZING THE AMPLIFIER


- Launch the "**ami-amp-config.exe**" software downloaded in step 1:




- ✓ If a security window appears, click on "*Additional Information*" and then "*Run Anyway*"




- Enter the IP address of the amp (192.168.0.1) in the window that appears, then click on "OK":




- A window will appear, showing the name and model of the amplifier – click on "OK":




- An alert window appears: "All your settings will be reset..." – click on "Yes":



- An update window scrolls for several seconds/minutes (depending on the amount of updates to be made):
 - ✓ If no firmware update is required, the next window appears after a few seconds, and the amplifier is immediately operational – click on "Exit"




- ✓ If necessary, the firmware updates automatically: the amplifier successively displays a black screen for a few moments while the files are being copied, then "*=>Files copied*", then "*=>Updating DSP(s)*" and finally "*Please RESTART*":




- Turn the amplifier off and on again. The update is complete, the amplifier is functional with AMi.

4. INSTALLATING AND LAUNCHING AMI

- Go to the website: <https://ami.arbane-groupe.com/ami/quickstart/index.html>
- Click on "Download":



- Double-click on the downloaded file "*Arbane AMI Setup.exe*". The software installs itself, and opens at the end of the installation.
- To discover how to use the software, please consult the **documentation** accessible directly from the software by clicking on "*About*", at the top right and then "*Documentation*":



NOTE: The documentation is also available on the AMI software download site (<https://ami.arbane-groupe.com/ami/quickstart/index.html>):

